

C. B. Fisk, Inc.

DESIGNERS & BUILDERS OF PIPE ORGANS

21 Kondelin Road
Gloucester, Massachusetts 01930-5108
TEL 978.283.1909 FAX 978.283.2938
EMAIL cbfisk@cbfisk.com
www.cbfisk.com



Opus 55

Old West Church

Boston, Massachusetts

29 voices, 46 ranks, 2,361 pipes

1971

Great, Man. II

Bourdon 16'
Prestant 8'
Spire Flute 8'
Octave 4'
Doublet 2'
Sesquialter II
Mixture IV-VI
Trumpet 8'
Clarion 4'

Choir, Man. I

Stopt Diapason 8'
Prestant 4'
Night Horn 4'
Nazard 2 2/3' *
Doublet 2'
Sharp IV
Cremona 8'

* hookdown adds 1 3/5'

Swell, Man. III

Violin Diapason 8'
Stopped Diapason 8'
Spitz Flute 4'
Cornet III
Furniture III
Contra Hautboy 16'
Trumpet 8'

Pedal

Bourdon 16'
Octave 8'
Rohrpipe 8'
Superoctaves 4' & 2'
Mixture III
Trombone 16'

COUPLERS

Choir to Great
Swell to Great
Swell to Choir
Great to Pedal
Choir to Pedal
Swell to Pedal

Tremulant
Balanced Swell Pedal
Crescendo Pedal
Wind Pressure: 2 1/4"

Casework contains many carvings and panels from a mid Nineteenth century Appleton organ found in Ipswich, MA. The main case is made from a 3 tower/2 flat case with missing cornices. The lower case, impost, tower tops and additional carvings are all new. The original case resembled the Choir case, which is entirely new. The new woodwork does contain a number of old panels.

In May and June 2000 the organ was extensively cleaned, 42 volt 3 phase slider motors replaced with solenoids and a modern 128 level combination action was added. Tonal regulation was focused upon the reeds.

Originally tuned in Equal Temperament the organ has been retuned into Vogel V and is presently in Fisk I, a nearly equal temperament developed by Charles Fisk for Opus 78, House of Hope Presbyterian Church, St. Paul MN, in 1979.

The present combination action has 8 generals (4 to thumb pistons & 4 to toe studs), 2 divisionals to each division. The Great tutti & Great cancel thumb pistons may be reprogrammed to become additional divisionals. The Great to Pedal reversible toe stud may be reprogrammed to reverse any combination of stops or couplers. Changes to the normal operation of the pistons can be done on any level of memory without affecting other levels. A builder's Crescendo and 3 programmable Crescendos are available. A simple sequencer, when engaged, converts all pistons into "Next" functions; the Great to Pedal is converted into "Back" function.